



Brother HL-2030 Laser printer

High quality mono printing from a compact, stylish machine.





Brother HL-2030 laser printer

The Brother HL-2030 is stylishly designed and compact enough to fit onto a shelf or workstation. It produces printouts with the speed and quality you would expect from a more expensive machine.

Simple

 $In stallation \ is \ straightforward-simply \ plug$ in the power cable, click through the installation CD, and you will be printing minutes later. Compatible with both PC and Apple systems, the HL-2030 uses a USB connection to ensure connectivity with most

Ample capacity

The 250 sheet paper tray provides ample capacity and there is also the option of a single sheet manual feed. With only a low cost toner cartridge and drum to replace you can be confident that this machine offers economical printing.

- Stylish & compact design
 Mac® & PC compatible
- Print speed of up to 16ppm
 USB connectivity
- Laser print quality HQ1200 (2,400 x 600dpi)
- Up to 250 Sheet Paper tray Single Sheet Manual Feed









Engine				
Technology Print Speed First Print Time Resolution	A4 Windows® 95/98/Me/NT®4.0/2000/XP Mac 0S® 9.1-9.2, Mac0S®X 10.2.4 or greater Linux	Electrophotographic Up to 16 ppm Less than 10 sec HQ1200 (2,400 × 600) / 600 / 300dpi 2000 / XP HQ1200 (2,400 × 600) / 600 / 300dpi 600 / 300 dpi		
Controller				
Processor Memory		SPARClite 96MHz 8MB		
Interface	Standard	Full-Speed USB2.0		
Network Connectivity Emulation	Wireless	Optional 802.11b wireless device (NC-2200w) USB TCP/IP ARP,RARP, BOOTP, DHCP, APIPA/Auto IP), WINS/NetBIOS, DNS, LPR/LPD, Raw Port/Port9100, SMB Print, IPP, FTP, mDNS,TELNET, SNMP, HTTP GDI		
Software				
Printer Driver	For Windows®	GDI Printer Driver for Windows® 98 / Me and 2000 / XP Brother Laser Driver for Mac 9.1-9.2, Mac 0S® X 10.2.4 or greater		
Utilities	For Linux (Download from http://solutions.brother.com)	GDI Printer Driver for Linux Interactive Help - Instructional movie for the solution when any error message appears on the Status Monitor.		
Control Panel				
Display Buttons	LED 1 button	4 LED (Toner/Drum/Paper/Ready) Go		
Paper Handling				
Paper Input	Manual Feed Slot Paper Tray 1 (Standard)	1 Sheet up to 250 Sheets can be stored in paper tray 1		
Paper Output	Face Down / Face up	up to 100 Sheets can be stored in the output tray face down (face up N/A)		
Duplex	Manual Duplex	Yes		

Media Specifications				
Media Types	Manual Feed Slot	Plain Paper, Bond Paper, Recycled Paper, Envelopes, Labels, and Transparencies		
	Paper Tray	Plain Paper, Bond Paper, Recycled Paper, Transparencies (up to 10 sheets)		
Media Weights	Manual Feed Slot	60 - 161 g/m2 (16 - 43 lb)		
	Paper Tray	60 - 105 g/m2 (16 - 28 lb)		
Media Sizes	Manual Feed Slot	Width 69.9 to 215.9 mm, Length 116 to 406.4 mm (Width 2.75" to 8.50", Length 4.57" to 16"")		
	Paper Tray	A4, Letter, B5(JIS), B5(ISO), A5, B6, A6, Exe		
Bright Control				

	Paper Tray	A4, Letter, B5(JIS), B5(ISO), A5, B6, A6, Exe			
Printer driver functions					
Page Layout Others	N in 1 Printing Poster Printing	Condense 2, 4, 9, 16 or 25 pages into 1 page Enlarge 1 page to print over 4, 9, 16 or 25 pages Quick Print Setup - A printer driver function that enables you to change the driver setting without opening Property dialog. Status Monitor - A function to indicate the printer error on the PC.			
Supplies					
Toner Drum	TN-2000 DR-2000	Starter: 1,500 A4/LTR pages @ 5% coverage Standard: 2,500 A4/LTR pages @ 5% coverage 12,000 A4/LTR pages (1 page / job)			

Dimensions / Weights				
Dimensions (W x D x H) Weights		371 x 361 x 165.5 mm 6.5kg		
Other				
Power Consumption	Printing	Less than 450W		
	Standby Sleep	Less than 70W Less than 5W		
Noise Level	Sound Pressure / Power Printing	Less than 51 dB(A) / Lwad 6.2B(A)		
	Sound Pressure / Power Standby	Less than 30 dB(A) / Lwad 4.3B(A)		
Ecology	Power Saving	Yes		
	Toner Saving	Yes		

Contact:

