


# Quick Setup Guide

Read the "REGULATIONS" sheet first to ensure that you use this printer safely. Read this "Quick Setup Guide" before you set up the printer.

- Before you can use the printer, you must set up the hardware and install the driver.
- Identify the operating system on your computer (Windows® 95 / 98 / Me, Windows NT® 4.0, Windows® 2000 / XP or Macintosh®).
- The interface cable is not a standard accessory. Please purchase the appropriate interface cable for the interface you intend to use (Parallel, USB or Network). Most existing parallel cables support bi-directional communication, but some might have an incompatible pin assignment or may not be IEEE 1284 compliant.
- If you are an Administrator, configure your network printer settings referring to the **Network Quick Setup Guide** (reverse side).

## Carton Components

Carton components may differ from one country to another. Save all packing materials and the printer carton. They should be used when shipping the printer. LJ3855001 Printed in Japan



## What is Included on the CD-ROM

You can find a Variety of Information on the CD-ROM.

**Windows®**

- Install Software**  
Install the printer driver and utilities. (Mac OS® X is not supported by Install Software.)
- Maintenance Tutorial**  
Instructional movie for printer maintenance.
- Documentation**  
View the User's Guide and Network User's Guide in PDF format. (Viewer included)
- Color PDF Print Samples**  
View color samples of printouts in PDF format.

**Macintosh®**

- Brother Solutions Center**  
The Brother Solutions Center (<http://solutions.brother.com>) is your one-stop resource for all your printer needs. Download the latest drivers and utilities for your printers, read the FAQs and troubleshooting tips, or learn about special print solutions.

# Setting Up the Printer

## Step 1 Install the Print Head Cartridge

- Remove all the packing tape.
- Push up button **A** to open the front cover.
- Push the orange button to open the paper outlet cover.
- Unpack the print head cartridge.
- Pull the 4 seals firmly to remove them completely. Remove the protective packing.
- Align the rollers of the print head cartridge with the slots, and then gently lower it into the printer.
- Remove the protective sheet. **Note:** Do not touch the black surface of the transfer roller.
- Close the paper outlet cover. Close the front cover.

## Step 2 Load Paper in the Paper Tray

- Pull the paper tray out until it stops. Lift up the front of the paper tray slightly and remove it from the printer.
- Remove the protective packing.
- Slide the side paper guides out. Lift the end paper guide and insert it into the slot of the paper size you want to load.
- Load paper in the paper tray. Make sure that all the paper is under the tabs.
- Align the side paper guides with the paper.
- Re-install the paper tray in the printer.

## Step 3 Install the Toner Cartridges

- Remove the top cover.
- Unpack the toner cartridge. Rock the toner cartridge 7 or 8 times.
- Insert the toner cartridge with the label side facing up. Match the cartridge color label to the corresponding label on the printer.
- Turn the levers by pressing down firmly and lock them to the **6** mark.
- Pull the toner seal straight up to remove it.
- Repeat Steps 2 to 5 for the remaining toner cartridges. Put the top cover back on.

## Step 4 Print a Printer Setting List

**Note:** When you want to change the language of the control panel message, refer to "Setting Your Language on the Control Panel" on the reverse side.

- Make sure the printer power switch is off. Do NOT connect the interface cable.
- Connect the AC power cord to the printer, and then plug it into the AC outlet.
- Turn on the power switch.
- After the printer warms up, the **Ready to Print** message will appear.
- Press **Menu** 3 times. Press **1: System**.
- Press **Form Feed** 3 times. Press **Printer Settings Printing**. The printer will now print the printer settings list.



# Network Quick Setup Guide

- If you are going to connect the printer to your network, we recommend that you contact your system administrator prior to installation.
- If you are an Administrator, configure your network printer settings referring to the following instructions.
- The default password for the print server is 'access'. You can use the BRAdmin Professional software or a web browser to change this password.



## Setting Your Language on the Control Panel

Ready to Print

- Press **Menu**.
- Press **Form Feed/Set**.
- Press **Form Feed/Set** 3 times.
- Press **Form Feed/Set**.
- Scroll through the available languages by pressing **Up/Down**.
- Press **Form Feed/Set** to accept the language. An asterisk ( \* ) appears.
- Press **Menu** to put the printer back into its Ready to Print state.

Ready to Print

## Setting Your Printer IP Address, Subnet Mask, and Gateway Address (Using the Control Panel)

**Note:** Your printer is configured to receive an IP address, Subnet mask and Gateway address from a DHCP server. If you do not use a DHCP server follow the steps below.

### Set Your IP Address Acquisition Method to Control Panel

Ready to Print

- Press **Menu**.
- Press **Form Feed/Set** 4 times.
- Press **Form Feed/Set**.
- Press **Form Feed/Set**.
- Press **Form Feed/Set**.
- Press **Form Feed/Set**.
- Press **Form Feed/Set**.
- Press **Form Feed/Set**.
- Press **Job Cancel/Back**.

TCP/IP Setup IP Address

### Setting Your Printer IP Address

Continued from the previous step

- Press **Form Feed/Set**.
- Press **Form Feed/Set**.
- Using **Up/Down**, set the desired value (for example, 192).
- Press **Form Feed/Set** and move the cursor to the next value.
- Repeat Steps 12 and 13 to finish setting your IP address.
- Press **Form Feed/Set**.
- Press **Form Feed/Set**.
- Press **Job Cancel/Back**.

TCP/IP Setup IP Address

TCP/IP IP Address

IP Address 000.000.000.000

IP Address 192.000.000.000

IP Address 192.000.000.000

IP Address 192.168.001.100

Reboot system to take effect

IP Address 192.168.001.100\*

TCP/IP IP Address

### Setting Your Subnet Mask

Continued from the previous step

- Press **Form Feed/Set**.
- Press **Form Feed/Set**.
- Set your subnet mask in the same way as the IP address.
- Press **Job Cancel/Back**.

TCP/IP IP Address

TCP/IP Subnet Mask

Subnet Mask 000.000.000.000

Reboot system to take effect

Subnet Mask 255.255.255.000\*

TCP/IP Subnet Mask

### Setting Your Gateway Address

Continued from the previous step

- Press **Form Feed/Set**.
- Press **Form Feed/Set**.
- Set your gateway address in the same way as the IP address.
- Restart the printer.

TCP/IP Subnet Mask

TCP/IP Gateway Address

Gateway Address 000.000.000.000

Reboot system to take effect

Gateway Address 192.168.001.254\*

## Network User's Guide Chapter Map

To configure the print server, refer to the Network User's Guide on the supplied CD-ROM.

OS	Configuration	Protocol	Chapter	Topic
Windows® 95/98/Me	Peer-to-Peer	TCP/IP	Chapter 3	Peer-to-Peer Printing
	Netware	NetBIOS	Chapter 4	NetBIOS Peer-to-Peer Printing
		IPX/SPX	Chapter 6	Novell Netware Printing
Windows NT®	Peer-to-Peer	TCP/IP	Chapter 2	TCP/IP Printing
	Netware	NetBIOS	Chapter 4	NetBIOS Peer-to-Peer Printing
		IPX/SPX	Chapter 6	Novell Netware Printing
Windows® 2000/XP	Peer-to-Peer	TCP/IP	Chapter 2	TCP/IP Printing
	Netware	NetBIOS	Chapter 4	NetBIOS Peer-to-Peer Printing
		IPX/SPX	Chapter 6	Novell Netware Printing
UNIX/Linux	Peer-to-Peer	TCP/IP	Chapter 2	TCP/IP Printing
	Netware	TCP/IP	Chapter 2	TCP/IP Printing
		IPX/SPX	Chapter 6	Novell Netware Printing
Macintosh®	Peer-to-Peer	TCP/IP	Chapter 1	UNIX Printing
	Netware	Apple Talk	Chapter 7	Apple Talk (Ether Talk)
		TCP/IP	Chapter 7	Apple Talk (Ether Talk)
OS2 Warp Server LAN Server	Peer-to-Peer	TCP/IP	Chapter 2	TCP/IP Printing
	Netware	NetBIOS	Chapter 4	NetBIOS Peer-to-Peer Printing

## For the Administrator (For Windows® Users Only)

### Install the BRAdmin Professional Configuration utility

The BRAdmin Professional software is designed to manage your Brother network connected devices. For example, Brother network ready printers and Brother network ready Multifunction devices can be managed using the BRAdmin Professional software. The BRAdmin Professional software can also be used to manage devices from other manufacturers whose products support the SNMP (Simple Network Management Protocol). For more information on the BRAdmin Professional utility go to <http://solutions.brother.com>

- Insert the CD-ROM into your CD-ROM drive. The opening screen will appear automatically.
- Click the Install Software icon on the Menu screen.
- Click "BRAdmin Professional." Follow the instructions on the screen.