

# **BUSINESS SMART SERIES**

# Print | Copy | Scan | Fax

# **All-In-One Business Inkjet Printer**

The professional A3 All-In-One that's built for business



# Key Features:

Full A3 capability for print, copy, scan, fax

Auto 2-sided print, copy, scan, fax

Fast print speeds of up to 22ipm mono and 20 ipm colour\*

9.3cm Touchscreen LCD

500 sheet paper input | 50 sheet ADF | 100 sheet Multi-Purpose tray

Wired, wireless and NFC connectivity

Easy to use, productive and robust, the MFC-J6935DW has been engineered to deliver dependable quality, meeting the needs of demanding office environments.

- New build design delivers a more robust and easy to operate device suited to a busy work environment
- A new and improved print head increases machine life and ensures exceptional durability

With advanced paper handling the MFC-J6935DW can handle a variety of media types whilst helping you to stay productive with fast prints speeds and a first page print in just 6 seconds.

- Stay prepared with a 500-sheet capacity paper tray and a 100 sheet multi-purpose tray for printing on a wide range of media
- Enjoy fast and hassle free scanning of multi-paged documents with the 50 sheet
   2-sided Automatic Document Feeder
- Reduce print costs and paper usage with automatic 2-sided print
- Auto paper low detection helps reduce downtime within a shared environment

Stand out with professional marketing materials and vivid office handouts. Whilst keeping print costs and replacement frequency down too with our optional high yield cartridges.

- Show off your sharp black text and vivid colour prints with new pigment based inks
- Save time and money with optional high yield cartridges that deliver yields up to 3,000 mono and 1,500 colour pages\*\*

Establish a 'tap to print' connection with added NFC connectivity and allow users to connect seamlessly in the office and on the go with Wi-Fi Direct™ for wireless printing from your smartphone, tablet, laptop or desktop, without the need for a router.

- Stay connected with smartphone, tablet, laptop and desktop compatibility
- With wireless and Wi-Fi Direct<sup>™</sup> you don't need a router to connect
- NFC allows for mobile print and scan from Android NFC devices and enables additional pull print solutions such as PrintSmart Secure Pro to be added\*\*\*\*

Capture and digitize paper documents directly from the 9.3cm touchscreen for electronic storage and sharing on the go.

- Scan to popular cloud storage facilities directly from the large 9.3cm intuitive swipe touchscreen
- Capture and convert documents with ease with our exclusive Brother Cloud Apps

#### General

| Inkjet   |
|--|
| 9.3cm colour touchscreen   |
| 512MB  |
| Hi-Speed USB 2.0   |
| 10Base-T/100Base-TX  |
| 802.11b/g/n (Infrastructure Mode)  |
| Supports both NFC cards (for secure authentication with pull print solutions like Brother PrintSmart Secure Pro) and Android NFC devices for mobile print and scan |
| Ink levels can easily be displayed on the LCD using the ink management menu  |
|  |

## **Colour Printer**

| Speed                          | 22ipm mono & 20ipm colour based on ISO/IEC 24734  |
|--------------------------------|---|
| Speed (Fast Mode)              | Up to 35 pages per minute mono & up to 27 pages per minute colour   |
| Warm-up Time                   | 0 seconds   |
| Resolution                     | Up to 1,200 x 4,800dpi  |
| 2- Sided Print                 | Yes   |
| Droplet Size                   | Minimum droplet size of 1.5pl   |
| Colour Enhancement             | Brother Image Enhancement allows the user to customise colour output  |
| FPOT<br>(First Print Out Time) | 6 seconds   |
| Print Languages                | PCL6, BR-Script3 (PostScript(R)3(TM) Language Emulation), PDF 1.7, XPS 1.0  |
| Embedded Fonts (PCL)           | 66 scalable fonts, 12 bitmap fonts  |
| Embedded Fonts (PostScript)    | 66 scalable fonts   |
| Embedded Barcodes (PCL)        | 16 bar codes* *Code39, Interleaved 2 of 5, FIM<br>(US-PostNet, Post Net (US-PostNet), EAN-8, EAN-<br>13, UPC-A, UPC-E, Codabar, ISBN (EAN, ISBN<br>(UPC-E), Code128 (set A, set B, set C), EAN128<br>(set A, set B, set C), Code93, GS1Databar, MSI |

#### **Printer Functions**

| N-up Printing <sup>3</sup>      | Reduce up to 2, 4, 9, 16 or 25 A4 pages into just one A4 page (Mac, up to 2, 4, 6, 9, or 16)  |
|---------------------------------|---|
| Poster Printing <sup>4</sup>    | Enlarge 1 A4 page into a poster using 4, 9, 16 or 25 A4 pages   |
| Watermark Printing <sup>4</sup> | Watermark your documents with predefined text or with your own user-defined messages  |
| Booklet Printing <sup>4</sup>   | Print documents in A5 booklet format using<br>automatic or manual 2-sided print   |
| Print Profiles <sup>3</sup>     | Store your favourite driver settings as profiles to<br>easily recall them (great for saving time and for<br>less technically adept users) |
| Print Archive <sup>4</sup>      | An electronic carbon copy feature that saves an<br>electronic copy of all printed documents as a<br>PDF file                              |
| Mono Only Mode                  | If a colour ink runs out, continue printing in Mono   |
|                                 |   |

# **Open Interface**

| Brother Solutions | Allows the use of 3 <sup>rd</sup> party solutions & apps, |
|-------------------|---|
|                   | such as PrintSmart Secure Pro to increase                 |
| Interface (BSI)   | security & productivity                                   |

#### **Printer Driver**

# **Mobile / Web Based Printing & Scanning**

| Brother iPrint&Scan<br>(Android)              | Print from, scan to, send faxes, preview received faxes, preview copies and check the machine status from an Android device              |
|---|--|
| Brother iPrint&Scan<br>(iPad / iPhone / iPod) | Print from, scan to, send faxes, preview received faxes, preview copies and check the machine status from an iPad / iPhone / iPod Touch. |
| Brother iPrint&Scan<br>(Windows® Phone)       | Print from and scan to a smart phone running the Windows® Phone Operating System   |
| Brother Print&Scan<br>(Windows® 8 & RT)       | Print from and scan to a Windows® 8 or Windows RT Tablet   |
| Google Cloud Print 2.0 <sup>6</sup>           | Print most common file types from any Google<br>Cloud Print enabled application  |
| AirPrint                                      | Print most common file types from any AirPrint enabled application   |
| Mopria  | Print most common file types from Mopria supported Android devices   |
| Brother Print Service Plugin                  | Print from Android devices without a dedicated App   |
| Evernote <sup>™6</sup>                        | Print from and scan to Evernote™ without using a PC  |
| Box <sup>6</sup>                              | Print from and scan to Box without using a PC  |
| Dropbox <sup>6</sup>                          | Print from and scan to Dropbox without using a PC  |
| Google Drive™ <sup>6</sup>                    | Print from and scan to Google Drive™ without using a PC  |
| OneDrive <sup>6</sup>                         | Print from and scan to Microsoft® OneDrive without using a PC  |
| Flickr <sup>®6</sup>                          | Print from and scan to Flickr® without using a PC  |
| Facebook® <sup>6</sup>                        | Print from and scan to Facebook® without using a PC  |
| Evernote™ <sup>6</sup>                        | Print from and scan to Evernote™ without using a PC  |
| OneNote <sup>6</sup>                          | Scan to Microsoft® OneNote without using a PC  |
|   |  |

<sup>&</sup>lt;sup>1</sup>Approx declared yield value in accordance with ISO/IEC 24711

<sup>2</sup>Calculated with 80g/m² paper

<sup>3</sup>Windows® & Mac® only

<sup>4</sup>Windows® only

<sup>5</sup>Optional free download from the Brother Solutions Centre <a href="http://solutions.brother.com">http://solutions.brother.com</a>

<sup>6</sup>Must be web connected

<sup>7</sup>Moximum number of printed pages per month can be used to compare designed durability between like Brother products. For maximum printer life, it is best to choose a printer with a duty cycle that for exceeds your print requirements

<sup>8</sup>It is recommended to use the straight paper output path and the quiet mode feature with paper weights over 105g/m2

<sup>9</sup>Requires Brother Software

#### **USB Host**

| Direct Print | Print directly from a USB flash memory drive. The supported file, JPEG, PDF  |
|--------------|--|
| Direct Scan  | Scan directly to a USB flash memory drive. The supported file formats include: PDF, PDF/A, Secure PDF, Signed PDF, JPEG, XPS, TIFF |

#### Scan

| r)               |
|------------------|
|                  |
|                  |
|                  |
|                  |
| P, FTP<br>can to |
| ogle<br>™,       |
| n, 1 to          |
| k                |
|                  |
| n                |
| r                |
| t                |
|                  |

#### **Scanner Driver**

| Windows®               | TWAIN, & WIA Windows® 8 (32 & 64 bit editions), Windows® 7 (32 & 64 bit editions), Windows Vista® (32 & 64 bit editions), |
|------------------------|---|
| Macintosh <sup>5</sup> | TWAIN & ICA<br>v10.9.5/10.10.x/10.11.x  |
| Linux <sup>5</sup>     | SANE(32 & 64 bit editions)  |

### Copy

| Speed – (A4) Mono/Colour         | Up to 12/9cpm (copies per minute)   |
|----------------------------------|---|
| Automatic 2-Sided Copying        | Yes   |
| FCOT<br>(First Copy Out Time)    | Less than 6 seconds from ready mode   |
| Resolution                       | Up to 600 x 600dpi  |
| Multi-Copying / Stack /<br>Sort  | Makes up to 99 copies of each page / Stacks or Sorts  |
| Enlargement / Reduction<br>Ratio | Reduce or Increase document sizes from 25% to 400% in 1% increments                             |
| N in 1 Copying                   | Allows the user to compress 2 or 4 pages on to a single A4 sheet                                |
| 2in1 ID Copying                  | Allows the user to copy both sides of an ID card to a single A4 sheet                           |
| Grey Scale                       | 256 shades of grey (8 bit)  |
| Outline & Copy <sup>6</sup>      | Draw around items to either copy a section or remove a section from the original document       |
| Enlarge Text Copy <sup>6</sup>   | Makes reading copied documents easier if the size of the text on the original document is small |

# Address Book<sup>5</sup>

| Speed Dials | 100 x2 locations for E-mail addresses   |
|-------------|---|
| Group Dial  | A combination of up to 6 groups can be stored for broadcasting                            |
| LDAP        | The ability to connect to an external LDAP enabled address book, like Microsoft® Exchange |

Address books are only accessible as part of the scan to email server function, available as an optional free download from the Brother Solutions Centre <a href="http://solutions.brother.com">http://solutions.brother.com</a>

<sup>&</sup>lt;sup>1</sup>Approx declared yield value in accordance with ISO/IEC 24711

<sup>2</sup>Calculated with 80g/m² paper

<sup>3</sup>Windows® & Mac® only

<sup>4</sup>Windows® only

<sup>5</sup>Optional free download from the Brother Solutions Centre <a href="http://solutions.brother.com">http://solutions.brother.com</a>

<sup>6</sup>Must be web connected

<sup>7</sup>Moximum number of printed pages per month can be used to compare designed durability between like Brother products. For maximum printer life, it is best to choose a printer with a duty cycle that for exceeds your print requirements

<sup>8</sup>It is recommended to use the straight paper output path and the quiet mode feature with paper weights over 105g/m2

<sup>9</sup>Requires Brother Software

#### Fax

| TUX  |  |
|--|--|
| Fax Modem                                      | 33,600bps (Super G3)   |
| Automatic 2-Sided<br>Faxing                    | Yes  |
| Internet Fax (iFax) <sup>5</sup>               | Fax documents anywhere in the world over the Internet without the use of a telephone line  |
| PC Fax Send <sup>9&amp;3</sup>                 | Send faxes directly from your PC   |
| PC Fax Receive <sup>9&amp;4</sup>              | Receive faxes directly to your PC  |
| Automatic Redial                               | Automatic redialling if the recipient fax is busy  |
| Telephone Index                                | An electronic, alphabetical listing of stored speed dials and group numbers  |
| Distinctive Ring Detection (UK & Denmark only) | An external service that allows two or more telephone<br>numbers shared on a single fixed line and use different<br>ring tones   |
| Speaker / Ring volume                          | 3 levels and off   |
| Fax / Tel Switch                               | Automatic recognition of fax and telephone reception   |
| Super Fine                                     | Enables quality transmission of very small print and line drawings   |
| Contrast                                       | Auto / light / dark  |
| Enhanced Remote Activate                       | Transfer a fax call, answered on an extension phone, to the fax machine  |
| Delayed Timer                                  | Up to 50   |
| Quick-Scan                                     | Reduce scanning times by scanning a fax into memory before sending. Approximately 2.5 seconds per page A4 standard resolution  |
| Memory Transmission                            | Up to 200 pages (ITU-T Test Chart, Standard Resolution, JBIG)  |
| Out of Paper<br>Reception                      | up to 200 pages (ITU-T Test Chart, Standard Resolution, JBIG)  |
| Dual Access                                    | Allows the operator to perform 2 different tasks on the machine at the same time   |
| Broadcasting                                   | Send the same fax message to up to 50 separate locations   |
| Batch Transmission                             | Stores documents for the same location in the machines memory for transmission in a single call  |
| Auto Reduction                                 | When receiving a single page document longer than A4 (297mm) the fax machine will automatically reduce the message to fit onto a single A4 sheet                             |
| ECM (Error Correction<br>Mode)                 | The MFC will detect line errors during fax transmission and resend the page(s) of the document that had an error (recipient machines must share this feature for it to work) |
| Fax Forwarding                                 | Sends a fax received in memory to another pre-<br>programmed fax number  |
| Remote Access                                  | Allows users to remotely access their machine  |
| Fax Retrieval                                  | Allows remote access to faxes stored in the machine  |
| Remote Set-up <sup>3</sup>                     | Allows users to set-up the MFC from their PC   |
| Grey Scale                                     | 256 shades (8 bit) of grey are available for faxing  |
| Fax Preview                                    | Preview received faxes on the screen   |
| Fax stamp                                      | Add the date and time to all received faxes  |
| •  |  |

### **Standard Paper Handling**

| Paper Input <sup>2</sup>  | Standard Tray – 250 sheets                            |
|---------------------------|---|
|                           | Lower Tray – 250 sheets                               |
|                           | Multi Purpose Tray – 100 sheets up to A4 or 10 sheets |
|                           | larger than A4  |
|                           | Automatic Document Feeder (ADF) – 50 sheets           |
| Paper Output <sup>2</sup> | Face up - 100 sheets                                  |
| Auto Paper Low Detection  | Standard and lower tray                               |
|                           |   |

## **Media Specification**

| Media Specification                |   |
|------------------------------------|---|
| Media Types & Weights <sup>8</sup> | Standard Tray – Plain, Inkjet, Glossy* & Recycled paper (between 64 - 220g/m², 260/m² when using Brother BP-71 Glossy Paper) *Glossy Up to A4 only Lower Tray – Plain & Recycled (between 64 - 120g/m²) Multi Purpose Tray - Plain, Inkjet, Glossy* & Recycled paper (between 64 - 220g/m², 260/m² when using Brother BP-71 Glossy Paper) *Glossy up to A3 Automatic Document Feeder (ADF) – plain & recycled paper (between 64 - 90g/m²) 2-sided Print - plain & recycled paper (between 60 - 120g/m²)   |
| Envelope Printing                  | Yes: Accuracy & reliability will depend on the quality & type of envelopes or labels used   |
| Media Sizes                        | Standard Tray - A3, LGR, LGL, A4, LTR, EXE, Folio, A5, A6, Photo(10x15cm), Indexcard(13x20cm), Photo-L(9x13cm), Photo-2L(13x18cm), Com-10, DL Envelope, Monarch, C5, Mexico Legal, India Legal Lower Tray - A4, LTR, A3, LGR, LGL, Folio, Mexico Legal, India Legal Multi Purpose Tray - A3, LGR, LGL, A4, LTR, EXE, Folio, A5, A6, Photo(10x15cm), Indexcard(13x20cm), Photo-L(9x13cm/3.5x5"), Photo-2L(13x18cm), Com-10, DL Envelope, Monarch, C5, Mexico Legal, India Legal Automatic Document Feeder (ADF) - Width: 105mm to 297mm x Length: 148mm to 431.8mm Scanner Glass -Up to Width: 297mm x Length: 431.8mm |

| Supplies                    |   |
|-----------------------------|---|
| Ink cartridges <sup>1</sup> | Black: LC3217BK 550 pages, LC3219XLBK 3,000 pages Cyan: LC3217C 550 pages, LC3219XLC 1,500 pages Magenta: LC3217M 550 pages, LC3219XLM 1,500pages Yellow: LC3217Y 550 pages, LC3219XLY 1,500 page |
| Carton Contents             | Ink cartridges , power supply cord, fax line cord, driver software for Windows®, Quick Set-Up Guide (PC interface cable NOT included)   |

The frequency of replacement consumables will vary depending on the complexity of the prints, the percentage of coverage, paper size, and the type of media.

<sup>&</sup>lt;sup>1</sup>Approx declared yield value in accordance with ISO/IEC 24711

<sup>2</sup>Calculated with 80g/m² paper

<sup>3</sup>Windows® & Mac® only

<sup>4</sup>Windows® only

<sup>5</sup>Optional free download from the Brother Solutions Centre <a href="http://solutions.brother.com">http://solutions.brother.com</a>

<sup>6</sup>Must be web connected

<sup>7</sup>Moximum number of printed pages per month can be used to compare designed durability between like Brother products. For maximum printer life, it is best to choose a printer with a duty cycle that for exceeds your print requirements

<sup>8</sup>It is recommended to use the straight paper output path and the quiet mode feature with paper weights over 105g/m2

<sup>9</sup>Requires Brother Software

#### **Network & Security**

| Network & Security              |   |
|---------------------------------|---|
| Wired Network                   | Built in Ethernet 10Base-T/100Base-TX   |
| Wireless Network                | IEEE 802.11b/g/n (Infrastructure Mode)  |
| Wi-Fi Direct <sup>™</sup>       | Print wirelessly without having to go through a wireless access point (both automatic and manual methods supported)   |
| Wireless Setup Support          | Wi-Fi Protected Setup (WPS)   |
| Network Protocols               | TCP/IP (IPv4 and IPv6)  |
| IPv4                            | ARP, RARP, BOOTP, DHCP, APIPA(Auto IP), WINS/NetBIOS name resolution, DNS Resolver, mDNS, LLMNR responder, LPR/LPD, Custom Raw Port/Port9100, IPP, FTP/FTPS Client FTP Server, SNMPv1/v2c/v3, TFTP server, SMTP Client, ICMP, Web Services (Print/Scan), CIFS Client, SNTP Client, POP3, LDAP, IMAP4, HTTP Server *POP3 & IMAP4 active only when Scan to Email Server is downloaded |
| IPv6 (off by default)           | NDP, RA, mDNS, LLMNR Responder, DNS Resolver, LPR/LPD, Custom Raw Port/Port9100, IPP, FTP/FTPs Client FTP , SNMPv1/v2c/v3 , TFTP server, Web Services (Print/Scan), SMTP Client, POP3*, CIF: Client, SNTP Client, LDAP, IMAP4*, ICMPv6, HTTP Server *POP3 & IMAP4 active only when Scan to Email Server is downloaded   |
| Wired Network Security          | APOP*, SMTP-AUTH, SSL/TLS (IPPS, HTTPS,FTPS,<br>SMTP, POP3*, IMAP4*), SNMP v3<br>802.1x (EAP-MD5, EAP-FAST, PEAP, EAP-TLS, EAP-<br>TTLS), Kerberos<br>*When Internet FAX is downloaded.   |
| Wireless Network Security       | WEP 64/128 bit, WPA-PSK (TKIP/AES), WPA2-PSK (AES), APOP*, SMTP-AUTH, SSL/TLS (IPPS, HTTPS, SMTP, POP3*, IMAP4*), SNMP v3, Kerberos, IPSec, 802.1x (LEAP, EAP-FAST, PEAP, EAP-TLS, EAP-TTLS) *When Internet FAX is downloaded.  |
| Wireless Certification          | WPA™/WPA2™ - Enterprise, Personal),<br>Wi-Fi Protected Setup (WPS)  |
| E-mail Notifications            | Automatically have the device send e-mail alerts when it requires attention, such as when the toner is low or needs replacing   |
| E-mail Reports                  | Receive usage reports on a regular basis via e-mail   |
| IP Filter                       | Restrict which network users can or cannot access the device over the network (IPv4 only)   |
| Secure Function Lock 3.0        | Restrict printing activity to individual or groups of users over a network. Can be used with PC User Login Name for up to 10 users  |
|                                 |   |
| Active Directory Authentication | N/A   |
| •                               | N/A   |
| Authentication                  |   |

### **Fleet Management Tools**

| Ability to centrally deploy and customise our drivers and software       |
|--|
| Modular installers that can be distributed through Active Directory®     |
| Web based print management software embedded onto the device             |
| LAN/WAN management software  |
| Easily create print drivers for hassle free deployment over your network |
| Professional print fleet management software sold exclusively by Brother |
|  |

# **Environment**

|                           | Operating - 29W   |
|---------------------------|-------------------|
| Power Consumption         | Ready – 6.5W      |
|                           | Sleep - 1.7W      |
|                           | Off - 0.04W       |
| Sound Pressure Level      | 50dB(A) (Approx.) |
| Sound Power Level         | 6.38B(A)          |
| Ink Save Mode             | Yes               |
| Energy Star               | Yes               |
| Blue Angel                | Yes               |
| Nordic Swan <sup>10</sup> | Yes               |
| GS mark                   | N/A               |
|                           |                   |

# **Dimensions & Weight**

| With Carton (WxDxH)    | 681 x 568 x 500mm TBDKG   |
|------------------------|---------------------------|
| Without Carton (WxDxH) | 575 x 477 x 374.5mm TBDKG |

# **Duty Cycles**

| Recommended Monthly          | 250 to 2,000 pages, monthly print volume |
|------------------------------|--|
| Maximum Monthly <sup>7</sup> | Up to 30,000 pages, monthly print volume |

<sup>&</sup>lt;sup>1</sup>Approx declared yield value in accordance with ISO/IEC 24711

<sup>2</sup>Calculated with 80g/m² paper

<sup>3</sup>Windows® & Mac® only

<sup>4</sup>Windows® only

<sup>5</sup>Optional free download from the Brother Solutions Centre <a href="http://solutions.brother.com">http://solutions.brother.com</a>

<sup>6</sup>Must be web connected

<sup>7</sup>Maximum number of printed pages per month can be used to compare designed durability between like Brother products. For maximum printer life, it is best to choose a printer with a duty cycle that far exceeds your print requirements

<sup>8</sup>It is recommended to use the straight paper output path and the quiet mode feature with paper weights over 105g/m2

<sup>9</sup>Requires Brother Software

<sup>10</sup>Nordic Swan certification is applicable in Nordic countries only